Software Design, Modelling and Analysis in UML

Lecture 17: Reflective Description of Behaviour, Live Sequence Charts I

2013-01-16

Prof. Dr. Andreas Podelski, Dr. Bernd Westphal

Albert-Ludwigs-Universität Freiburg, Germany

Course Map Mode $\mathcal{Y} = (\mathcal{Z}, \mathcal{C}, V, atr)$. SM expr CD, SM op Si G = (N, E, f)**Mathematics**

Contents & Goals

- Last Lecture:

 Herarchisto State Machines

 Later: Remaining pseudo-states, such as shallow/deep history; active vs. passive;
 behavioural feature.

This Lecture:

- Educational Objectives: Capabilities for following tasks/questions.
 What does this LSC mean?
 Are this UML model's state machines consistent with the interactions?
 Please provide a UML model which is consistent with this LSC.
 What is: activation, hot/cold condition, pre-chart, etc.?

Reflective description of behaviour.

Sociomore and abstract syntax.

I.SC concrete and abstract syntax.

Soft intuitive semantics.

Symbolic Blichi Automata (TBA) and its (accepted) language.

2)74

You are here.

Recall: Constructive vs. Reflective Descriptions

[Harel, 1997] proposes to distinguish constructive and reflective descriptions:

 "A language is constructive if it contributes to the dynamic semantics of the model. That is, its constructs contain information needed in executing the model or in translating it into executable code." A constructive description tells **how** things are computed (which can then be desired or undesired).

Motivation: Reflective, Dynamic Descriptions of Behaviour

"Other languages are reflective or assertive, and can be used by the system modeler to capture parts of the thinking that go into building the model – behavior included –, to derive and present views of the model, statically or during occurrion, or to set constraints on behavior in preparation for verification."
A reflective description tells what shall or shall not be computed.

Note: No sharp boundaries!

5/74

6,74

Recall: What is a Requirement?

- $\bullet \ \, \text{The semantics of the UML model} \, \mathcal{M} = (\mathscr{CD},\mathscr{SM},\mathscr{OD}) \, \, \text{is the transition} \\ \text{system} \, (S, \to, S_0) \, \text{constructed according to discard/dispatch/commence-rules}.$
- \bullet The computations of $\mathcal{M},$ denoted by $[\![\mathcal{M}]\!],$ are the computations of $(S,\to,S_0).$

A reflective description tells what shall or shall not be computed.


More formally: a requirement θ is a property of computations, sth. which is either satisfied or not satisfied by a computation

$$\pi = (\sigma_0, \varepsilon_0) \xrightarrow{(cons_0, Snd_0)} (\sigma_1, \varepsilon_1) \xrightarrow{(cons_1, Snd_1)} \cdots \in \llbracket \mathcal{M} \rrbracket,$$

denoted by $\pi \models \vartheta$ and $\pi \not\models \vartheta$, resp.


Interactions: Problem and Plan

- Then (conceptually) $\pi \models \vartheta$ if and only if $w_{\pi} \in \mathcal{L}(\mathcal{I})$.



In general: $\forall (\exists) \ \pi \in [\![\mathcal{M}]\!] : \pi \models (\not\models) \ \vartheta$ Problem: what is " \models " and what is " ϑ "?

- Define the language $\mathcal{L}(\mathcal{I})$ of an interaction \mathcal{I} via Büchi automata. Define the language $\mathcal{L}(\mathcal{M})$ of a model \mathcal{M} basically its computations. Each computation $\pi \in [\![\mathcal{M}]\!]$ corresponds to a word w_π .




10/74

Interactions: Plan

- In the following, we consider Sequence Diagrams as interaction \mathcal{I} ,
- more precisely: Live Sequence Charts [Damm and Harel, 2001]. • We define the language $\mathcal{L}(\mathcal{I})$ of an LSC via Büchi automata.
- Then (conceptually) $\pi \models \vartheta$ if and only if $w_{\pi} \in \mathcal{L}(\mathcal{I})$.

Why LSC, relation LSCs/UML SDs, other kinds of interactions: later.



OCL as Reflective Description of Certain Properties the inthe (o,E)-pai in m

• invariants: $\mathcal{H} \models \mathcal{V} \quad \text{if} \qquad \forall \pi \in [\![\mathcal{M}]\!] \ \forall i \in \mathbb{N} : \pi^i \models \vartheta,$

non-reachability of configurations:

 $\iff \forall \, \pi \in \llbracket \mathcal{M} \rrbracket \, \forall \, i \in \mathbb{N} \colon \pi^i \models \neg \vartheta$ $\nexists \, \pi \in \llbracket \mathcal{M} \rrbracket \, \nexists \, i \in \mathbb{N} : \pi^i \models \vartheta$

reachability of configurations:

 $\iff \neg(\forall \pi \in \llbracket \mathcal{M} \rrbracket \ \forall \ i \in \mathbb{N} : \pi^i \models \neg \vartheta)$ $\exists\,\pi\in[\![\mathcal{M}]\!]\,\exists\,i\in\mathbb{N}:\pi^i\models\vartheta$

• ϑ is an OCL expression or an object diagram and • " \models " is the corresponding OCL satisfaction or the "is represented by object diagram" relation.

In General Not OCL: Temporal Properties

Dynamic (by example)

- reactive behaviour $* \text{ "for each C instance, each reception of E is finally answered by F'} \\ \forall \pi \in [\![M]\!] : \pi \models \theta$

$$\forall \, \pi \in [\![\mathcal{M}]\!] : \pi \models \vartheta$$


non-reachability of system configuration sequences
$$\text{ "there mustri't be a system run where C first receives E and then sends F' at $\pi \in [M]: $\pi \models \theta$}$$


 \bullet reachability of system configuration sequences \bullet "there must be a system run where C first receives E and then sends F " $\exists \pi \in \llbracket \mathcal{M} \rrbracket : \pi \models \vartheta$

But: what is " \models " and what is " ϑ "?

Live Sequence Charts — Concrete Syntax

12/74






Example


ASVERTISEMENT:
Lether Real-Time
Systems Summer
2013

- Whenever the CrossingCrt has consumed a 'scereq' event
 then it shall finally send 'lights.on' and 'barrier.down' to lights.Crt and Barrier.Crt,
 if Lights.Crt is not operational when receiving that even the set of this comario desen't apply; maybe then's another LSC for that case.
- if LightsCtrl is operational when receiving that event,
 it shall reply with 'lights ok' within 1-3 time units.
- the BarrierCtrl shall reply with 'barrier_ok' within 1-5 time units, during this time (dispatch time not included) it shall not be in state 'MvUp'.
- ullet After having consumed both, CrossingCtrl may reply with 'done' to the environment. $14/^n$ 'lights_ok' and 'barrier_ok' may occur in any order.



Intuitive Semantics: A Partial Order on Simclasses

(i) Strictly After:




Intuition: A computation path violates an LSC if the occurrence of some events doesn't adhere to the partial order obtained as the transitive closure of (i) to (iii). $^{18/n}$

(iii) Explicitly Unordered: (co-region)

(ii) Simultaneously: (simultaneous region)

Partial Order Requirements




- Whenever the CrossingCut has consumed a "secret" event
 then it shall finally send nights.orn and barrier down to lights.Cri and BarrierCorl.
 if LightsCut is not "operational" when receiving that event,
 the rest of this scenario doesn't apply; maybe there's another LSC for that case.

- the BarrierCtrl shall reply with 'barrier_ok' within 1–5 time units, during this time (dispatch time not included) it shall not be in state 'MvUp'.
- 'lights_ok' and 'barrier_ok' may occur in any order.
- \bullet After having consumed both, CrossingCtrl $\rm may$ reply with 'done' to the environment. $~19_{/\rm N}$

LSC Specialty: Modes

With LSCs,

- whole charts,locations, andelements
- have a mode one of hot or cold (graphically indicated by outline).




LSC Specialty: Activation

One major defect of MSCs and SDs: LSCs: Activation condition ($AC \in Expr_{\mathscr{T}}$), they don't say when the scenario has activation mode ($AM \in \{init, inv\}$), to/may be observed.

Intuition: (universal case) e given a computation π , whenever expr holds in a configuration (a_k, b_k) of $\{Pr = which is initial, i.e. <math>k = 0, \ or$ $(AM = mixial) = whose k is not further restricted, <math display="block">(AM = mixinl) = and \ if the pre-chart is observed from k to <math>k + n$, then the main-chart has to follow from k + n + 1.


22)74

Example: What Is Required?




- Whenever the CreakingCrit has consumed a "secret" earn!
 then it shall finally send "lightscon" and "barrier Jovn" to LightsCrit and Barrier Crit.
 I LightsCrit is not "operational when recoving that events.
 the rest of this scenario doesn't apply, maybe there's morther LSC for that case.
 i LightsCrit is operational when recoking that event.
 i tabal steply with "lightscak" within 1-3 time units.
- the BarrierCtrl shall reply with 'barrier_ok' within 1–5 time units, during this time (dispatch time not included) it shall not be in state 'MvUp'.
- 'lights_ok' and 'barrier_ok' may occur in any order. • After having consumed both, CrossingCtrl may reply with 'done' to the environment. $23_{/N}$

Example: Modes



- Whenever the CrossingCrt has consumed a "secret" event
 ethan it shall finally send "lights.orl" and "barrier.cloon" to Lights.Crt and Barrier.Crt,
 et Light.Crt is not operational when neceiving that event.
 the rest of this scenario doesn't apply, maybe there's another LSC for that case.
 et Light.Crt is "operational" when neceiving that event,
 it shall reply with "light.cole" within 1-3 time units.
- the BarrierCtrl shall reply with 'barrier_ok' within 1–5 time units, during this time (dispatch time not included) it shall not be in state 'MvUp',
- 'lights_ok' and 'barrier_ok' may occur in any order.
- ullet After having consumed both, CrossingCtrl may reply with 'done' to the environment. 21_{74}

Course Map



24/74

73/74

References

| Damm and Harel, 2001| Damm, W. and Harel, D. (2001). LSCs: Breathing life into Message Sequence Charts. Formal Methods in System Design, 19(1):45–80. |
| Harel, 1997| Harel, D. (1997). Some thoughts on statecharts, 13 years later. In Grumberg, O., editor, CAV, volume 1234 of LVCS, pages 226–231. Springer-Verlag, O., editor, CAV, volume 1234 of LVCS, pages 226–231. Springer-Verlag, Elevation of London, 2007| Harel, D. and Maco, S. (2007). Assert and negate evisited: Modal semantics for UMI sequence diagrams. Scrivate and System Modeling (SoSyM). To appear. (Early version in SCESM'06, 2006, pp. 13-20). |
| Harel and Marelly, 2003| Harel, D. and Marelly, R. (2003). Come, Let's Play: Scrauric-Stead Programming Using LSCs and the Pagk-Tengine. Springer-Verlag, Scrawic-Stead Programming Using LSCs and the Pagk-Tengine Springer-Verlag, Scrawic-Stead Programming Using LSCs and Pagk-Tengine Springer-Verlag, Scrawic-Stead Programming Using LSCss and Pagk-Tengine Springer-Verlag